

# Nite Cell Lamp

## Installation Instructions



Luminaire's light distribution is direct.

**LED**

Denotes which light source/light sources that can be supplied with the luminaire.



**IP40**

IP Classification: Product is IP40: Protected against solid objects over 1mm (tools, wires and small wires).



Class 2: Double insulated electrical appliances designed in such a way that they do not require a safety connection to ground



**RISK OF FIRE:** (a) The minimum clearance distance from the top of the luminaire to any normally flammable building element is 100mm. (b) The minimum clearance distance from the top of the luminaire to any building insulation is 100mm. (c) The minimum clearance distance from the side of the luminaire to any normally flammable building element is 100mm. (d) The minimum clearance distance from the side of the luminaire to any building insulation is 100mm. **WARNING – RISK OF OVERHEATING OR FIRE IF THE CLEARANCE DISTANCES ARE COMPROMISED.**



RCM: Indicates a device's compliance with applicable ACMA technical standards.



ESD: Personnel should be grounded when unpacking or handling the luminaire.

## Important Information

Please read this guide carefully before installing or maintaining this equipment. Data should be used as an INDICATION only and good electrical practices should be followed at all times.

Must only be installed by a licensed electrician.

If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer or their service agent or a similar qualified person in order to avoid a hazard.

For indoor use only.

A qualified electrician, in accordance with AS/NZS 3000:2007 wiring regulations should carry out connection to mains wiring.

Ensure that the rated voltage and frequency requirements are compatible with the available mains supply, 220-240V 50Hz.

Cleaning of reflectors and lenses should be carried out using clean, soft and lint free cloths and anti-static cleaning fluid.

Do not carry out high voltage insulation test i.e. 500/1000V this may damage the fixtures electrical components.

This fitting is designed in such a way as to minimise the risk of it being used as a ligature attachment point. The risk assessment and management procedures must be viewed as part of a comprehensive prevention strategy which includes clinical risk management

## Skin Installation

1. Secure the concrete skin into the form work, ensuring the the face of skin finish's level with the concrete.
2. Brace the internals of the skin to prevent any distortion caused by the weight of the wet concrete.
3. Concrete finish level must be level with the outer face of the skin.

## Luminaire Installation

1. Unfasten the security fasteners (bit T25 with pin) to remove the frame and diffuser. Then remove the gear tray.
2. Lift the luminaire into the skin, feeding the supply cable through the cable entry hole.
3. Secure the luminaire onto the skin using the fasteners supplied in the skin.
4. Complete electrical connection and re install the gear tray to the luminaire.
5. Align the frame and diffuser mounting holes with the mounting holes in the body. Refasten all of the frame fasteners to the body.
6. For Anti-Ligature applications, it is the responsibility of the installer to seal the luminaire to the wall with suitable Anti-Pick Mastic (or similar).

This installation instruction is relevant to the standard version of the above family. Customised variants may have mechanical changes or may have changed mounting procedures.